



4-Port USB Charging Adapter, USB Type-C™



Quick Installation Guide

DA-10195 Rev 2.0

1.0 INTRODUCTION

The Digitus® 4-Port USB Charging Adapter, USB Type-C™ is the universal charging station for all your devices. The USB-C charging port (max. 5-20V/3A/60W) with Power Delivery (PD) 3.0 functionality is used to quickly and efficiently recharge ultrabooks, laptops, tablets, smartphones, mobile game consoles, etc. Use three USB-A charging ports (total: 5V/2.4A, each of which can deliver max. 5V/2.4A) to charge any kind of mobile devices such as smartphones, tablets, power banks, speakers, etc. The total output power is 72W.

2.0 FEATURES

- Internal chip allows the 100-240V AC of input voltage.
- Four USB connectors outputs:
 - 3x USB A ports, provide 5V/2.4A in total, every port provides 5V/2.4A (max), and equipped with intelligent IC and automatically identifies the handheld devices attached to the USB port
 - 1x USB-C port with 5V/9V/15V/20V DC and 3A output
- Accurate limited current output and over current protection.
- Overload protection and over voltage protection.
- Short circuit protection.
- Over temperature protection and remove the fault condition auto-recovery.
- Select precision electrical components, fire line version, and imported fire plastic.
- Portable and convenient to use.
- Specially designed for your Type-C supported devices.



3.0 SPECIFICATIONS

Input/Output	
Input	100-240VAC 50/60Hz
Output	USB-A: 5V/2.4A USB-C: 5V, 9V, 15V, 20V/3A
Protection	
Over current	Yes
Short circuit	Yes
Over temperature protection	Yes
Over voltage Protection	Yes
Performance	
AC Leakage Current	0.25mA max at 240VAC input
Ripple And Noise	≤250mV
Turn on delay time	3s max
Rise time	20mS
Efficiency	USB-A: ≥80% USB-C: ≥81.4%
Mechanical	
Color	Black
Size	91*75*27.5mm
Weight	220g (main unit, without power cord)
Environmental	
Operating Temperature Range	0~40°C
Storage Temperature Range	-20 ~ 80°C
Operating Relative Humidity	5% ~ 90% RH

4.0 PACKAGE CONTENTS

Before attempting to use this unit, please check the packaging and make sure the following items are contained in the shipping carton:

- Main unit×1
- Power Cord×1
- User Manual×1

5.0 OPERATION

Operation Procedures

- 1.** Plug the DC connector of power adapter into the interface of the power station; and then plug the other connector of power adapter into socket.
- 2.** Plug one USB connector of the cable into the interface of the charger and plug the other connector of the cable into the electronic device (notebook, smartphone, tablet, etc.)
- 3.** Please pull the USB connector out after the electronic equipment's fully charged.

* All brand names and logos which mentioned above are trademarks or registered trademarks of the respective owner.

Operation Notes

1. For optimum performance, please use the power station according to the user manual.
2. Please plug the power adapter into socket whose voltage range should be 100~240VAC.
3. Please unplug the power adapter after using.

Note: Our products have protection functions and the two tips above are suggestions just for safety.

4. Do not use the power station with an electronic product which is not in conformity with the specifications, so as to avoid any problems caused by specification mismatching.
5. It's normal that power adapter and power station will be a little overheated in the use process.
6. When the power station stops working under over-current, over-temperature or short-circuit protection, please unplug the device after it automatically returns to work, then you need to check whether the device is compatible with this charger.
7. Do not let the power station close to fire, such as stove, candles and etc.
8. Do not let the power station soak into liquid, such as swimming pool, bathtub, etc.
9. Do not wash the power station with corrosive cleaner.
10. If the power station cannot work properly, please contact the store or distributor in your area.

6.0 CONNECTION DIAGRA



Hereby Assmann Electronic GmbH, declares that the Declaration of Conformity is part of the shipping content. If the Declaration of Conformity is missing, you can request it by post under the below mentioned manufacturer address.

www.assmann.com

Assmann Electronic GmbH
Auf dem Schüffel 3
58513 Lüdenscheid
Germany

